

Very intuitive to use, the FAST3 is the easiest way to control your emergency or auxiliary equipment.

Ergonomic and adapted to all circumstances.

Features :

- 1 Cable BUS
- Quick Installation
- No relay, no fuse
- Key Backlighting, **configurable colors**
- Interlock Function
- Automatic Standby
- Manual Configuration
- Operating Voltage : +10VDC to +30VDC
- 4 Positive Power Outputs
- 2 Negative Outputs, 2 Positive Inputs, 1 Negative Input



Special included features :

- Very compact Power Module
- Provided with a collection of pictograms

Easy fastening system.

Console designed to be positioned in various places in the vehicle.

Specifications :

A single BUS cable from the dashboard of the vehicle to simplify and limit the installation time Integrated and configurable functions to reduce installation time by up to 50%.

The complete elimination of relays and fuses increases the reliability of your electrical installations.

The buttons on the console are backlit and the color can be configured to ensure high legibility in all circumstance.

The FAST3 is configurable to enable interlock function for blue lights, siren, Grill lights & many more

The product is equipped with an automatic "standby" function which can be controlled by the position of the ignition key

All options are configurable directly from the keyboard

All IDEATEC Products operates on voltage from +10VDC to +30VDC

Technical information :

| P/N Reference | Operating voltage | Global max current | Digital Inputs | Outputs | Quiescent current | Operating temp C° | Power Module Dimension (mm) | Console Dimensions (mm) | Conformity CEM R10 |
|---------------|-------------------|--------------------|------------------|-----------------------------|-------------------|-------------------|-----------------------------|-------------------------|--------------------|
| P0050F0200 | +10VDC to +30VDC | 20A | 2x POS 1x NEG | 4x POS (10A) 2x NEG (1A) | 5 mA | -25°C to +60°C | 94 x 73 x 26 | 102 x 26 x 38 | R10 |